



# PSU test report

*Bernhard Woerndl-Aichriedler  
bwa@xdevelop.at*

## 1 Contents

- General information
- Point of operation
- Standby power consumption
- Load testing
- Turn on voltage
- Conducted EMI
- Overload testing

## 2 General information

Testing the following device

Manufacturer: Vigortronix  
Device name: VTX-214-005-112  
Serial number: 1  
Nominal voltage: 12.000V  
Nominal current: 0.420A  
Tester: Bernhard Woerndl-Aichriedler <bwa@xdevelop.at>  
Start time: 14-Jul-2016 00:03:18



### 3 Point of operation

The test has been conducted with the following conditions

Voltage/Frequency: 250V-50Hz  
Ambient Temperature: 31.48C





## 4 Standby power consumption

Voltage: 250.69V

Frequency: 50Hz

-----  
Current: 0.003249A

-----  
P active: 0.174W

P apparent: 0.815VA

P reactive: 0.796VAR

P factor: 0.214

-----  
Output voltage: 12.085V



## 5 Load testing

Characteristics

Voltage: 250.68V

Frequency: 50Hz

Loads: 0.000A to 0.420A

-----  
Minimum output voltage: 12.030V

Maximum output voltage: 12.189V

Regulation error absolute: -0.030V/+0.189V


Regulation error relative: -0.2%/+1.6%


-----  
Vpp ripple&noise absolute: 0.520V


Vpp ripple&noise relative: 4.3%

-----  
RMS ripple&noise absolute: 0.099V

RMS ripple&noise relative: 0.8%









## 6 Turn on voltage

Testing when the PSU enables it's output

```
Test load: 0.042A
Test Frequency: 50Hz
Threshold: 9.000V
-----
Turn-on voltage: 60.00V
-----
Output voltage: 12.175V
```





## **7 Conducted EMI**

No EMI test results

## **8 Overload testing**

No overload test results